



NOTES:

1. SUPPORT POST – USE ANY OF THE FOLLOWING :
 - 2-3" MIN. STEEL PIPE CAPPED AND CEMENTED IN GROUND
 - 2-3" MIN. GALV. STEEL I-BEAM (3/8"-1/2" THICK) CEMENTED IN GROUND
 - 2-3" MIN. CHANNEL IRON CEMENTED IN GROUND
2. MOUNTING HARDWARE – TWO 12 GAUGE 1-5/8" X 1-5/8" CONTINUOUS SLOT HOT DIPPED GALVANIZED CHANNEL (e.g., UNISTRUT) COMPLETE WITH 1-1/4" X 5/16" DIA. 13 THD SPRING NUT (2 PER CHANNEL), 5/16" HEX NUT, AND LOCK WASHER SECURELY MOUNTED TO SUPPORT POSTS.
3. PRE-FABRICATED METER PEDESTAL MAY BE SUBSTITUTED FOR 1 & 2 ABOVE. CONTACT REGION METER MANAGER.
4. WHEN USING DIRECT BURIAL CABLE, USE THE "ALTERNATE".
5. CUSTOMER DISCONNECT PER NEC.
6. CUSTOMER SECURITY LIGHT CAN BE INSTALLED ON THE POLE IF A CLEARANCE OF 2'-0" MIN. ABOVE OR BELOW WEATHERHEAD IS MAINTAINED AND COMPANY APPROVAL IS OBTAINED.
7. FOR IDENTIFICATION PURPOSES, THE SOCKET (INSIDE & OUT) AND BREAKER MUST BE PERMANENTLY AND PLAINLY MARKED TO DESIGNATE THE ADDRESS NUMBER BEING SERVED.
8. METER SOCKET MAY BE CONNECTED TO AN EXTERNAL GROUND ROD, IF REQUIRED BY LOCAL INSPECTION AUTHORITIES.
9. FOR CUSTOMER/COMPANY RESPONSIBILITIES SEE COMPANY SPECIFIC SERVICE GUIDE EXHIBIT 19.

**SINGLE MOBILE HOME SERVICE
OVERHEAD & UNDERGROUND**

FirstEnergy

Service Guide

REV.

6

EXHIBIT 12

DATE

12/07